

## Sensor Activated Flushometers

## Description

Concealed, Sensor Activated Royal® Model Water Closet Flushometer with True Mechanical Override, for rear spud bowls.

## Flush Cycle

Model 152-1.6 ES-S TMO Low Consumption (1.6 gpf/6.0 Lpf)

### Specifications

Quiet, Concealed, Diaphragm Type, Rough Brass Closet Flushometer with the following features:

- PERMEX™ Synthetic Rubber Diaphragm with Dual Filtered Fixed Bypass
- OPTIMA® EL-1500-L Self-Adaptive Infrared Sensor with Indicator Light
- "Walk By" Delay of Eight (8) Seconds Prevents Unintentional Flushes
- User friendly three (3) second Flush Delay
- Courtesy Flush™ Non-Hold-Open True Mechanical Override
- Non-Hold-Open Integral Solenoid Operator
- Die Cast Sensor Plate with no visible Fasteners (for 2-gang Electrical Box)
- 1" I.P.S. Wheel Handle Bak-Chek® Angle Stop
- Adjustable Tailpiece
- High Back Pressure Vacuum Breaker Connection with Hex Coupling Nut and Spud Coupling for 11/2" Rear Spud
- Sweat Solder Adapter
- High Copper, Low Zinc Brass Castings for Dezincification Resistance
- Non-Hold-Open Integral Solenoid Operator, Fixed Metering Bypass and No External Volume Adjustment to Ensure Water Conservation
- Flush Accuracy Controlled by CID™ Technology
- Hydraulic Metal Push Button Assembly for True Mechanical Override
- Diaphragm, Stop Seat and Vacuum Breaker molded from PERMEX™ Rubber Compound for Chloramine Resistance

Valve Body, Cover, Tailpiece and Control Stop shall be in conformance with ASTM Alloy Classification for Semi-Red Brass, Valve shall be in compliance with the applicable sections of ASSE 1037. Installation conforms to ADA requirements.

### **Variations**

 $\Box$  TP Trap Primer

### Accessories

Transformer (120 VAC/24 VAC 50 VA) □ EL-154 □ EL-342 Transformer (240 VAC/24 VAC 50 VA)

See Accessories Section and OPTIMA® Accessories Section of the Sloan catalog for details on these and other OPTIMA® Flushometer variations.

Consult Sloan for Sloan brand matching fixture options.

This space for Architect/Engineer approval	
Job Name	Date
Model Specified	Quantity
Variations Specified	
Customer/Wholesaler	
Contractor	
Architect	



## Automatic

Sloan OPTIMA® equipped Flushometers provide the ultimate in sanitary protection and automatic operation. There are no handles to trip or buttons to push. The Flushometer operates by means of an infrared sensor that adapts to its surrounding. Once the user enters the sensor's effective range and then steps away, the Flushometer Solenoid initiates the flushing cycle to flush the fixture.

User makes no physical contact with the Flushometer surface except to initiate the Override Button when required. Helps control the spread of infectious diseases. 24-Hour Sentinel Flush keeps fixture fresh during periods of nonuse.

### Economical

Automatic operation provides water usage savings over other flushing devices. Reduces maintenance and operation costs.

Solid state electronic circuitry assures years of dependable, trouble-free operation. The operational components of the Flushometer are identical to a handle activated Royal® Flushometer, proven by over 100 years of experience

# Warrantv

3 year (limited)

### Patent Pending







# 152-1.6 ES-S TMO

### Description

Concealed, Sensor Activated Royal® Model Water Closet Flushometer with True Mechanical Override, for rear spud bowls.

### Flush Cycle

Model 152-1.6 ES-S TMO Low Consumption (1.6 gpf/6.0 Lpf)

### ELECTRICAL SPECIFICATIONS

### Control Circuit

Solid State 24 VAC Input 24 VAC Output 8 Second Arming Delay 3 Second Flush Delay 24-Hour Sentinel Flush

### OPTIMA® Sensor Range

Nominal 22" - 42" (559 mm - 1067 mm) Self-adaptive Window:  $\pm$  10" (254 mm)

# Solenoid Operator


24 VAC, 50/60 Hz

### Transformer

Sloan Part #EL-154 120 VAC, 50/60 Hz Primary 24 VAC, 50/60 Hz Secondary Class II, UL Listed, 50 VA.

Sloan Part #EL-342 240 VAC, 50/60 Hz Primary 24 VAC, 50/60 Hz Secondary Class II, UL Listed, 50 VA.


# WIRING DIAGRAM




One Transformer serves up to ten (10) OPTIMA® Closet/Urinal Flushometers. Specify number of transformers required accordingly.

### **OPERATION**

 A continuous, invisible light beam is emitted from the OPTIMA® Sensor.




2. As the user enters the beam's effective range (22" to 42") the beam is reflected into the OPTIMA® Scanner Window and transformed into a low voltage electrical circuit. Once activated, the Output Circuit continues in a "hold" mode for as long as the user remains within the effective range of the Sensor.




**ELECTRICAL BOX INSTALLATION** 

3. When the user steps away from the OPTIMA® Sensor, the circuit waits 3 seconds (to prevent false flushing) then initiates an electrical "one-time" signal that operates the Solenoid. This initiates the flushing cycle to flush the fixture. The Circuit then automatically resets and is ready for the next user.



### **ROUGH-IN**



Position of Sensor Box can be raised or lowered 1" (25 mm) if in conflict with Handicap Grab Bars.

# 4" (102 mm) SQ. x 2-1/2" (64 mm) DEEP OUTLET BOX **FINISHED** - APPĹETON ELECT. #4SD1 MOUNTING PLATE OR EQUAL (BY CONTRACTOR) TILE WALL EL-592 COVER PI ATF FINISHED PLASTER WALL 4" (102 mm) SQ. BOX DEVICE ATTACH MOUNTING PLATE TO PLASTER COVER (PLASTER RING) 3/4" (19 mm) HIGH — APPLETON ELECT. #8470 RING USING FOUR (4) SCREWS (SUPPLIED)

# SLOAN VALVE COMPANY • 10500 SEYMOUR AVENUE • FRANKLIN PARK, IL 60131

Phone: 1-800-982-5839 or 1-847-671-4300 • Fax: 1-800-447-8329 or 1-847-671-4380 • www.sloanvalve.com

OR EQUAL (BY CONTRACTOR)