

18v X2 LXT® Lithium-Ion (36v) Brushless Cordless String Trimmer, Tool Only

Model XRU07Z

ZERO EMISSIONS AND REDUCED MAINTENANCE; NO NEED FOR GAS OR OIL

- Makita-built Outer Rotor BL™ Brushless Motor direct-drive system provides high power and increased torque
- Constant Speed Control minimizes reduction in rotation speed under load
- 2-speed options (Low: 0-5,000 RPM, High: 0-6,500 RPM) allows the operator to match the speed to the application
- Delivers up to 60 minutes of run time under load on the low speed setting using two 18V LXT° 5.0Ah BL1850 batteries*

*Under Load: 13-3/4" cutting swath with .080" nylon line, approximate run time will vary according to grass conditions



POWER



Makita-built Outer Rotor BL™ Motor direct-drive system provides high power and increased torque

SPEED



2-speed options (Low: 5,000 RPM, High: 6,500 RPM) allows the operator to match speed to application

CONVENIENCE



Zero emissions and reduced maintenance; no need for gas or oil

COMFORT



Weighs only 9.9 lbs. with batteries (batteries not included) for reduced operator fatigue

NO CORD & ZERO EMISSIONS

18v X2 LXT® Lithium-Ion (36v) Brushless Cordless String Trimmer, Tool Only

Model XRU07Z

FEATURES & BENEFITS


- Zero emissions and reduced maintenance; no need for gas or oil
- Direct-drive motor mounted directly on the trimmer head for increased efficiency and improved tool balance
- Efficient BL™ Brushless motor is electronically controlled to optimize battery energy use for up to 50% longer run time per charge
- The BL™ Brushless Motor eliminates carbon brushes, enabling the BL™ Motor to run cooler and more efficiently for longer life
- 13-3/4" cutting swath for user convenience
- Weighs only 9.9 lbs. with batteries (batteries not included) for reduced operator fatigue
- Bump and Feed trimmer head rotates clockwise to help direct grass clippings away from operator
- BL™ Brushless motor delivers up to 6,500 RPM for faster cutting
- Extreme Protection Technology (XPT) is engineered for improved dust and water resistance for operation in harsh job site conditions
- Reverse rotation system allows operator to quickly clear trimmer head of entangled grass and weeds
- Electric brake for maximum productivity
- 3-stage L.E.D. gauge indicates battery charge level
- Equipped with Star Protection Computer Controls™ to protect against overloading, over-discharging and over-heating
- Rapid Optimum Charger communicates with the battery's built-in chip throughout the charging process to optimize the battery life by actively controlling current, voltage and temperature
- Rapid Optimum Charger has a built-in fan to cool the battery for faster, more efficient charging
- Only use genuine Makita batteries and chargers

STANDARD EQUIPMENT

- Goggles (195243-2)
- Hex Wrench (783217-7)
- Hex Wrench (783202-0)
- Accessory Bag (831304-7)
- Bump & Feed Trimmer Head

SPECIFICATIONS

| Cutting Capacity | 13-3/4" |
|---------------------------|----------------------------|
| No Load Speed | 5,000/6,500 RPM |
| Battery | 2X 18V X2 LXT® Lithium-lon |
| Overall Length | 69" |
| Net Weight (with battery) | 9.9 lbs. |
| UPC Code | 088381-689151 |





OPTIONAL ACCESSORIES

 18V Lithium-lon Rapid Optimum 4-Port Charger (DC18RD)





18V LXT® Lithium-lon
5.0Ah Battery (BL1850)





Makita offers a wide variety of accessories. For a complete listing, please refer to the Makita General Catalog or visit our website at **makitatools.com**, or call **1-800-4MAKITA**.



